

# 905U-L I/O Transmitter & Receiver pair

Powerful, flexible, easy to use industrial wireless I/O



## Description

The ELPRO 905U-L products are a small I/O count transmitter and receiver pair delivered pre-configured for ease of installation. Just connect the antennas and apply power for them to be operational. The L series products may be reconfigured into a wider ELPRO I/O or gateway network as application needs grow. DIN rail mounted and DC (9-30V) powered, the units can also power a loop powered device to 24VDC, 30mA.

## Features

- Small I/O capability- use where a simple one-way link is required.
- Uni-directional, one way communications.
- Transmitter and receiver units factory-configured as a matching pair, or user-configurable as part of a larger wireless I/O network.
- Secure data encryption.
- WIB-net intelligent wireless protocol, peer-to-peer communications, immediate exception reporting plus configurable high-scan updates, multi-hop mesh repeater.
- Up to 3000 wireless units per network
- Power supply 9 – 30VDC, 24VDC analog loop supply internally generated.
- RS232 Configuration and diagnostics port
- Compatible with the 905U Wireless I/O and Wireless Gateway family.
- Class 1 Div 2 hazardous areas approval.

## 905U-L-T Transmitter Unit

- Powerful 900MHz frequency hopping 1W transmitter.
- External inputs - two digital/pulse inputs, one analog input (0-20mA, 4-20mA), and one thermocoupleV input.
- Internally calculated values - analog and thermocouple setpoint status, pulse count, power supply voltages.
- Thermocouple input –20 to +100mV with cold-junction compensation and linearization for J, K, T or E-type.
- Local output for setpoint status: generated by comparin analog input to high and low setpoints.
- RS232 Configuration and diagnostics port.

## 905U-L-R Receiver Unit

- Three digital contact outputs and one analog output (0-20mA, 4-20mA).
- Communications failure indication and configurable output.
- Outputs can be configured as retained or reset (fail-safe) on communications failure.
- LED indication of radio signal strength

## Specifications

| SPECIFICATION                          | DESCRIPTION   |
|--|---|
| <b>Transmitter (905U-L-T) Inputs</b>   |   |
| Digital/Pulse Input                    | Two inputs, suitable for voltage free contacts / NPN, or voltage input 0-1 VDC on / >3 VDC off. Pulse input max rate 10 Hz, 50 msec on time, pulse input counted as 2 x 16 bit register.  |
| Analog input,                          | 0-20 mA, 4-20mA, span and zero configurable (default 4-20mA), "floating" differential input, resolution 16 bit, accuracy < 0.1 %.   |
| Thermocouple input,                    | -20mV to +100mV, J, K or T type linearization with on-board cold-junction compensation, accuracy better than 1degC.   |
| Analog & thermo-couple setpoint status | Setpoint status sets (on) when input value < low setpoint and resets (off) when input value > high setpoint, status transmitted as per digital input, setpoint values are settable via front-panel rotary switch or configuration software. |
| <b>Receiver (905U-L-R) Outputs</b>     |   |
| Digital Output                         | Three relay contact outputs, 260VAC, 1A rating  |
| Analog Output                          | 0-20mA, 4-20mA, configurable span and zero default (4-20mA), source output, 12-bit resolution, 0.1% accuracy.   |
| Comms-Fail,                            | Internal status based on configurable time-out value. Comms-fail output. ok output, FET, 30VDC, 500mA   |
| Fail-safe                              | On "comms-fail", outputs user-configurable as retained (last correct value) or reset (fail-safe).   |
| <b>Wireless</b>                        |   |
| Radio                                  | Frequency hopping spread spectrum 902-928MHz, sub-bands available, 1W Approved to FCC Part 15.247, RS210.   |
| Range                                  | Line of sight range 20 miles (4W ERP), 15km (1W ERP); 3000 ft / 1000 m in obstructed industrial environments.   |
| Repeaters                              | Radio distances can be increased by up to 5 intermediate repeater units.  |
| Transmissions                          | Each transmission may be configured to be sent 1 to 5 times.  |
| <b>Communications</b>                  |   |
| Protocols                              | ELPRO WIB-net wireless protocol, enabling peer-to-peer communications. Input values are transmitted on immediate change plus timed updates (maximum rate 5 times per second).   |
| Encryption                             | Wireless messages are data encrypted for security protection.   |
| <b>Power</b>                           |   |
| Power Supply                           | 9-30VDC.  |
| Power Consumption                      | @12VDC  |
| Receiver                               | 100mA   |
| Transmitter (Idle)                     | 40mA  |
| Transmitter (TX)                       | 300mA   |
| Analog Loop Supply                     | Internally generated, 24VDC 30mA  |

| SPECIFICATION                        | DESCRIPTION   |
|--------------------------------------|---|
| <b>Serial Port</b>                   |   |
| RS232                                | RJ45 female DCE, used for configuration and diagnostics.  |
| Reported diagnostics                 | RSSI, comms logging, I/O status   |
| <b>LED Indication</b>                |   |
| Transmitter unit.                    | Power/OK, Radio TX, DIN1, DIN2, Analog Setpoint status.   |
| Receiver unit.                       | Power/OK, Radio RX, DO1, DO2, DO3, Communications fail LED's also used to provide radio signal strength indication  |
| <b>Configuration and Diagnostics</b> |   |
|                                      | Factory configuration transmitter/receiver matched pair. User configuration via serial port. Unidirectional units can be configured to network with Mult-I/O and Gateway units. Diagnostics features – read input values, write output values, radio signal strength, monitor communication messages. |
| <b>Compliance</b>                    |   |
| EMC                                  | 89/336 EEC, AS3548, FCC Part 15, EN301489   |
| RF (radio)                           | EN 300 220, Part 15.247, RSS-210, AS4295, AS4768.1  |
| Hazardous area                       | Class 1 Div 2 (USA/Canada)  |
| Safety                               | EN 60950  |
| <b>General</b>                       |   |
| Size                                 | 3.9" x 0.9" x 4.7" (100 mm x 22 mm x 120 mm)  |
| Housing                              | Thermo-plastic enclosure.   |
| Mounting                             | DIN rail mounting   |
| Terminal blocks                      | Removable; max. conductor 14 AWG 0.1 in. <sup>2</sup> (2.5 mm <sup>2</sup> )  |
| Antenna connector                    | 1 x SMA female standard polarity  |
| Temperature rating                   | -40 to 60°C / -40 to 140°F  |
| Humidity rating                      | 0–99% RH noncondensing  |
| Weight                               | 0.6 lbs (0.3 kg)  |

**Note:** Specifications are subject to change.

## Ordering

| PRODUCT CODE                | DESCRIPTION   | FREQUENCY   | RF POWER |
|-----------------------------|---|-------------|----------|
| EL-905U-L-T-AU or NZ or XX  | I/O Radio (Transmitter Only) I/O = (2)DI/PI + (1)AI + (1)TCI                        | 915–928 MHz | 1W       |
| EL-905U-L-R-AU or NZ or XX  | I/O Radio (Receiver Only) I/O = (3)DO+ (1)AO  | 915–928 MHz | 1W       |
| EL-905U-L-P1-AU or NZ or XX | I/O Radio Kit: (1)905U-L-T + (1)905U-L-R paired radios + (2)DG900-1 + (1)xSER-RJ45  | 915–928 MHz | 1W       |
| EL-905U-L-P2-AU or NZ or XX | I/O Radio Kit: (1)905U-L-T + (1)905U-L-R paired radios + (2)CFD890EL + (1)xSER-RJ45 | 915–928 MHz | 1W       |
| EL-905U-L-P3-AU or NZ or XX | I/O Radio Kit: (1)905U-L-T + (1)905U-L-R paired radio No Antennas + (1)xSER-RJ45s   | 915–928 MHz | 1W       |

**Notes:** Available RF power and frequency may vary depending on country of application.

## Accessories

| PRODUCT CODE             | DESCRIPTION  |
|--------------------------|--|
| <b>Antennas 900 MHz</b>  |  |
| DG900-1/5                | Whip antenna, SMA male, angle bracket, –2 dBi gain, 3' (1m) coaxial cable      |
| WH900-SMA                | Whip antenna, SMA male, –2 dBi gain  |
| CFD890EL                 | Dipole antenna, SMA male, mounting bracket, 2 dBi gain, 16' (5m) coaxial cable |
| SG900EL                  | Collinear antenna, N-type female, 5 dBi gain                                   |
| SG900-6                  | Collinear antenna, N-type female, 8 dBi gain                                   |
| YU6-900                  | Yagi antenna, N-type female, 9 dBi gain  |
| YU16-900                 | Yagi antenna, N-type female, 15 dBi gain                                       |
| <b>Cables</b>            |  |
| CC3/10/20-SMA            | Coaxial cable kit, 9.8' (3m)/32' (10m)/65' (20m), N-type to SMA                |
| CCTAIL-SMA-F/M           | Coaxial cable tail, 24" (600 mm), SMA to N-type female/male                    |
| ETH-C5X                  | Serial cable, 6' (1.8m), crossover, RJ-45 to RJ-45                             |
| ETH-C5A                  | Serial cable, 6' (1.8m), direct, RJ-45 to RJ-45                                |
| SER-DB9                  | Serial RS-232 cable, DB-9 male to DB-9 female, straight through                |
| SER-RJ45                 | RS-232 serial cable, DB-9 female to RJ-45                                      |
| <b>Surge Diverters</b>   |  |
| CSD-SMA-2500             | SMA surge diverter for use with CC10/CC20-SMA                                  |
| CSD-N-6000               | Coaxial surge diverter, bulkhead N-female to N-female                          |
| MA15/D/1/S1              | Power supply surge diverter, 110 Vac/15A                                       |
| <b>Power Supplies</b>    |  |
| PS-DINAC-12DC-OK         | DIN rail power supply, 100–250 Vac, 12 Vdc/5A                                  |
| PS-DINAC-24DC-OK         | DIN rail power supply, 85–264 Vac, 24 Vdc/2.5A                                 |
| <b>Mounting Brackets</b> |  |
| BR-COL-KIT               | Mounting bracket kit for collinear antenna                                     |
| BR-YAG-KIT               | Mounting bracket kit for Yagi antenna  |
| MA15/D/1/S1              | Power supply surge diverter, 110 Vac/15A                                       |
| MA15/D/2/S1              | Power supply surge diverter, 240 Vac/15A                                       |
| IOP32D                   | Signal surge diverter, 2 x 2-wire/1 x 4-wire                                   |
| <b>Power Supplies</b>    |  |
| PS-DINAC-12DC-OK         | DIN rail power supply, 100–250 Vac, 12 Vdc/5A                                  |
| PS-DINAC-24DC-OK         | DIN rail power supply, 85–264 Vac, 24 Vdc/2.5A                                 |
| <b>Mounting Brackets</b> |  |
| BR-YAGI-KIT              | Mounting bracket kit for Yagi antenna  |
| BR-COL-KIT               | Mounting bracket kit for collinear antenna                                     |

ELPRO Technologies  
29 Lathe St  
Virginia, QLD 4014  
Australia  
[www.elpro.com.au](http://www.elpro.com.au)

Telephone:  
Global:+61 7 3352 86  
USA: +1 855 443 5776

© 2021 ELPRO  
All Rights Reserved

ELPRO Technologies Inc  
2028 East Ben White Blvd,  
#240-5656 Austin, TX 78741-6931  
USA

Telephone:  
USA: +1 855 443 5776

© 2021 ELPRO  
All Rights Reserved



ELPRO Technologies is a registered trademark.

All other trademarks are property  
of their respective owners.